

MADE-TO-ORDER CRYSTAL FILTERS

SPECIMEN FILTER DESIGN - 4



Tel: +44(0)1460 230000
 Fax: +44(0)1460 230001
 Email: sales@euroquartz.co.uk
 Web: www.euroquartz.co.uk

174.0MHz Crystal Filter

A high frequency filter in a small, low-profile package.

General Specification

Centre Frequency:	174.00MHz
Insertion Loss:	6dB max.
Ripple:	1dB max.
Bandwidth 3dB:	± 40 kHz nominal
173.9375MHz	30dB min.
173.875MHz	45dB min.

Outline and Dimensions

